

(19)  **Europäisches Patentamt**
European Patent Office
Office européen des brevets



(11) **EP 1 096 608 A2**

(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
02.05.2001 Bulletin 2001/18

(51) Int. Cl. 7: **H01R 9/24**

(21) Application number: 00123068.9

(22) Date of filing: 24.10.2000

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

(30) Priority: 25.10.1999 JP 30319599
31.03.2000 JP 2000099098

(71) Applicant: Omron Corporation
Kyoto-shi, Kyoto (JP)

(72) Inventors:
• Kamel, Takashi,
Omron Corporation
Shiokouji-dori, Shimogyo-ku, Kyoto-shi (JP)
• Imai, Kiyoshi,
Omron Corporation
Shiokouji-dori, Shimogyo-ku, Kyoto-shi (JP)


• Sato, Toshinori,
Omron Corporation
Shiokouji-dori, Shimogyo-ku, Kyoto-shi (JP)
• Miyoshi, Kazuaki,
Omron Corporation
Shiokouji-dori, Shimogyo-ku, Kyoto-shi (JP)
• Shimokawa, Satoru,
Omron Corporation
Shiokouji-dori, Shimogyo-ku, Kyoto-shi (JP)

(74) Representative:
Kilian, Helmut, Dr.
Wilhelms, Kilian & Partner
Patentanwälte
Eduard-Schmid-Strasse 2
81541 München (DE)

(54) **Sensor system and connector used therefor**

(57) A sensor system includes a plurality of sensor bodies (1) arranged aligned and adjacent to each other, each of said sensor bodies being connected to an electric cord (8, 9) including at least a signal line via a connector (2, 3). Each connector (2, 3) has a power feed terminal, and a detachable fitting for electrically connecting the power feed terminals of the connectors is provided between the connectors. The power supplied to the connector (2, 3) of any of the sensor body (1) through the power feed line in the electric cord (8, 9) is distributed to the power feed terminal of another sensor body (1) through a row of connectors. By this configuration, the number of power feed lines for the overall system can be significantly reduced, and common bodies not distinguished for the main and sub bodies can be used as the sensor bodies (1), whereby the cost can be reduced and inventory management can be facilitated. Further, when any of the sensor bodies fails, it is possible to simply exchange the failed sensor body (1) only, while maintaining the use of the electric cord that has been used.

FIG. 1



EP 1 096 608 A2

Description

BACKGROUND OF THE INVENTION

Field of the Invention

[0001] The present invention relates to a sensor system in which a plurality of sensor bodies of a number of head separation type sensors (for example, fiber type photoelectric sensors, ultrasonic sensors, proximity sensors and the like) are arranged aligned with each other by means of a DIN (Deutsche Institute Normenausschuss) rail or the like.

Description of the Background Art

[0002] In the technical field of FA (Factory Automation), for example, head separation type sensors (for example, fiber type photoelectric sensors, ultrasonic sensors, proximity sensors and the like) are widely used to detect presence/absence and positions of objects. When a fiber type photoelectric sensor is used, for example, a sensor head for emitting and receiving a detection beam (red light beam, infrared ray or the like) is placed in a narrow space near an object of detection, while a sensor body containing a light emitting element and a light receiving element is accommodated in a control panel placed away from the object of detection, with the sensor head and a sensor body coupled by an optical fiber. Generally, the outer shape of the sensor body casing is a thin rectangular cube. When a number of sensor bodies are to be accommodated in the control panel, the bodies are typically arranged in contact with each other to form a row, using the DIN rail.

[0003] Fig. 17 schematically shows an example of a sensor system in which sensor bodies of fiber type photoelectric sensors (hereinafter simply referred to as "sensor bodies") are arranged in contact with each other to form a row. As can be seen from the figure, on a DIN rail 401 mounted in the control panel, a plurality of sensor bodies 402₁, 402₂, 402₃, ... 402_n for detecting different objects are arranged in a row in the transverse direction. From a front surface of each of the sensor bodies 402₁, 402₂, 402₃, ... 402_n, optical fibers 403 and 404 constituting outgoing and returning paths for the detection beam, respectively, are drawn out, and from the rear end surface of the case, an electric cord 405 including a power feed line 405a and a signal line 405b (see Fig. 18) is drawn out.

[0004] When a detection beam path 408 is opened for transmission or intercepted between sensor head portions 403a and 404a at the tip ends of optical fibers 403 and 404, internal circuitry of the sensor body functions, and a detection signal (a switching signal or an analog signal corresponding to the amount of received light) is externally output through the signal line 405b in the electric cord 405. The detection signal is supplied as a control input, to a programmable logic controller (PLC)

407, as shown in Fig. 18.

[0005] Further, as shown in Fig. 18, power supply from a power source 406 to each of the sensor bodies 402₁, 402₂, 402₃, ... 402_n is effected through the power feed line 405a. Power feed line 405a includes two, that is, positive and negative, lines.

[0006] In this manner, in the conventional photoelectric sensor systems in which a number of sensor bodies 402₁, 402₂, 402₃, ... 402_n are arranged aligned with each other and in contact with each other, it is necessary to supply power to each of the photoelectric sensor bodies 402₁, 402₂, 402₃, ... 402_n through power feed line 405a in the electric cord. Therefore, for the electric cord, a cord having a large number of core lines is necessary, and, in addition, it takes time and labor just to connect these lines.

[0007] A structure saving lines in this type of photoelectric sensor system has been known, as described in Japanese Patent Laying-Open No. 9-64712. According to the technique described in this Laid-Open Application, the sensor system includes one main sensor (body) and a plurality of sub sensors (bodies) arranged in a row and in contact with the main sensor and with each other. An electric cord including both the signal line and the power feed line is main sensor, and an electric cord including the signal line only is connected to each sub sensor, by joining means that will fix the position such as solder. On the side surfaces of the cases of the main and sub sensors, there are a male junction and female junction to provide interface between neighboring sensors. When the main sensor is connected to a sub sensor and the neighboring sub sensors are connected to each other by connected to the these joints, the power supplied to the main sensor through the electric cord is successively passed through a conductor in each sensor case, to the series of sub sensors.

[0008] In the sensor system described in Japanese Patent Laying-Open No. 9-64712, feeding and receiving of power through the conductors in the sensor cases through the male and female joints connecting the neighboring sensor bodies with each other is possible, whereby the reduction of lines can be achieved, as power supply to individual sub sensor through the electric cord is made unnecessary.

[0009] In such a sensor system, however, two different sensor bodies, that is, one having such a structure that receives external power through the electric cord, and one having such a structure that receives power through the male and female joints from the neighboring sensor body are necessary. This means that the number of parts and the steps of parts management increase, resulting in increased cost. Further, inventory management of the sensor bodies is troublesome, as there are two different types of the sensor bodies.

[0010] Further, when trouble occurs in any of the sensors (main or sub), it becomes necessary to change the electric cord connected to the defective sensor at the same time. This requires time consuming and trou-

blesome work of disconnecting the bundle of electric cords and newly connecting substitute electric cords, and material waste increases.

SUMMARY OF THE INVENTION

[0011] An object of the present invention is to provide a sensor system which can significantly reduce the number of power feed lines in the overall system, which enables a decrease in costs and simplified inventory management by adopting sensor bodies of common structure not distinguished for the main or sub sensor, and, in case any malfunction occurs in any of the sensor bodies, enables exchange of the defective sensor body only, while the electric cords that have been used so far can be maintained.

[0012] Another object of the present invention is to provide a connector system which can flexibly cope with increase/decrease of the number of sensors arranged, when a plurality of sensor bodies are to be arranged in a row, and which can maintain minimum number of power feed lines regardless of the number of sensors to be arranged.

[0013] A further object of the present invention is to provide a main connector suitable for implementing the above described power feed connector system.

[0014] A still further object of the present invention is to provide a sub connector suitable for implementing the above described power feed connector system.

[0015] The above described objects can be attained by the sensor system in accordance with the present invention, including a plurality of sensor bodies arranged aligned and adjacent to each other, and a plurality of connectors detachably coupled to the sensor bodies and detachably coupled to neighboring connectors.

[0016] Here, "sensor" includes head separation type sensors such as a fiber type photoelectric sensor, an ultrasonic sensor, a proximity sensor and the like. Generally, the sensor system of this type consists of the sensors of the same type. The present invention, however, is also applicable to a sensor system in which various sensors mentioned above are used mixed with each other.

[0017] The sensor body is provided with a joint for the connector enabling detachable coupling with the corresponding connector, and the connector is provided with a joint for the sensor body enabling detachable coupling with the corresponding sensor body.

[0018] The "joint for the connector" on the sensor body includes at least a power receiving terminal for receiving, from the connector, the power to be fed to the internal electric circuitry. Here, "at least" means that there may possibly be one, two or more signal terminals in addition to the power receiving terminal.

[0019] The "joint for the sensor body" on the connector includes at least a power feed terminal for feeding power to the internal electric circuitry of the sensor

body. Here again, "at least" is used to include possible additional terminals.

[0020] The sensor body and a connector are detachably coupled through the joints of each other. When the sensor body and a connector are coupled, the power receiving terminal of the joint for the connector is electrically connected to the power feed terminal of the joint for the sensor body. Thus, a power feed path from the connector to the sensor body is established.

[0021] Preferably, the direction of attachment/detachment when a sensor body and a connector are coupled is orthogonal to the direction of coupling between the sensor bodies with each other. This arrangement facilitates attachment/detachment between the sensor body and a connector, without the necessity of providing a large space between the sensors. Further, it may be preferred if a specific sensor body is detachable, while the coupled state of the connector is maintained.

[0022] Here, "a plurality of connectors" includes at least one main connector and one or two or more sub connectors. In other words, there may be two or more main connectors.

[0023] The main and sub connectors are provided with a joint for neighboring connector, enabling detachable coupling with the neighboring connectors.

[0024] The "joint for the neighboring connector" of the main connector includes at least a power feed terminal for supplying the power introduced from the power supply line to a neighboring connector.

[0025] The "joint for the neighboring connector" of the sub connector includes a joint for the neighboring connector including at least a power receiving terminal for receiving power from one neighboring connector, and a joint for the neighboring connector including at least a power feed terminal for feeding the power received by the power receiving terminal to another neighboring connector.

[0026] The neighboring connectors are detachably coupled through the joints for the reciprocal neighboring connectors. At this time, the power feed terminal provided in the joint for the neighboring connector of one connector is electrically connected to the power receiving terminal provided in the joint for the neighboring connector of the other connector. Thus, a power feeding and receiving path from one connector to the other connector is established.

[0027] More specifically, the main connector and a sub connector are detachably coupled through the joint for the neighboring connector of the main connector and the joint for the neighboring connector of the sub connector. At this time, the power feed terminal of the main connector is electrically connected to the power receiving terminal of the sub connector. Thus, a power feeding and receiving path from the main connector to the sub connector is established.

[0028] The sub connector coupled to the main connector and another sub connector adjacent to this sub

connector are detachably coupled through the joints for the neighboring connectors of themselves, and at this time, the power feed terminal of that sub connector which is next to the main connector is electrically connected to the power receiving terminal of that sub connector which is next to the sub connector.

[0029] By successively coupling one or a plurality of sub connectors to at least one main connector, a row of connectors is formed, and a series of power feeding and receiving path starting from the main connector is established.

[0030] Preferably, the joint for the neighboring connector of the main connector is provided on the side surface only on which a neighboring connector exists, and not on the other side surface. Therefore, when the main connector is arranged at an end of a row of sensors, the power feed terminal is not exposed at the side where the neighboring connector does not exist. Therefore, the risk of an electrical short-circuit or receiving an electric shock by accidentally touching the power feed terminal can be avoided.

[0031] Each joint for the neighboring connector of the main and sub connectors has a connecting structure for establishing mechanical and electrical connections with the neighboring connector. Here, the power receiving terminal and the power feed terminal of each joint for the neighboring connector are included in the connecting structure for establishing the electrical connection.

[0032] Preferably, the connecting structure of the joint for the neighboring connector including a power receiving terminal of the sub connector preferably has a projecting portion protruding to a connector neighboring the joint. The connecting structure of the joint for the neighboring connector of the main connector and of the joint for the neighboring connector of the sub connector including the power feed terminal has a recessed portion receiving the projecting portion of the connector neighboring the joint, and the connecting structure does not have the projecting portion protruding toward the neighboring connector. In such a structure, the connecting structure of connector does not protrude from either end of the row of sensors. As there is no projection on either end of the row of sensors, it becomes possible to arrange other device not requiring power connection by the connector in tight contact with the row of sensors. Further, the situation where an operator's clothes or the like are accidentally caught on the projection or something hitting the projection can be avoided.

[0033] The main connector is connected to an electric cord including at least a power feed line, and the main connector includes an internal conductor for leading the power supplied from the electric cord to the power feed terminal provided at the joint for the sensor body and to the power feed terminal provided at the joint for the neighboring connector, inside the main connector.

[0034] More specifically, in the main connector, the

power introduced from the electric cord is supplied through the internal conductor to the power feed terminals of the joint for the sensor body and a joint for the neighboring connector and further, the power is passed to the sensor body and to the power receiving terminal of the neighboring sub connector, from the power feed terminals.

[0035] Further, the sub connector includes an internal conductor for leading the power received through the power receiving terminal provided at one joint for the neighboring connector to the power feed terminal provided at the joint for the sensor body and to the power feed terminal provided at the other joint for the neighboring connector, within the sub connector.

[0036] More specifically, in the sub connector, the power received by the power receiving terminal is supplied through the internal conductor to the power feed terminal provided at the joint for the sensor body and to the power feed terminal provided at the joint for the neighboring connector, and further, from these power feed terminals to the neighboring connector and the power receiving terminal of the sensor body.

[0037] In this manner, by coupling an arbitrary number of sub connectors to the main connector, it becomes possible to feed the power fed to the main connector through the electric cord to each sensor body through the row of connectors.

[0038] The sensor system of the present invention provides a power feed line by means of a connector system including a main connector to which an electric cord including at least a power feed line is connected, and one or a plurality of sub connectors electrically connected to the main connector. Therefore, simply by coupling the main connector and the sub connector to the sensor bodies and by coupling neighboring connectors with each other, the power can be supplied to each sensor body. Therefore, the power feed line have only to be connected to the main connector, and hence the power feed line is unnecessary for the sub connectors. Therefore, the number of lines for the overall system can be reduced.

[0039] Further, as the connector and a sensor body can be detachably coupled, it is possible, when any trouble occurs in the sensor body, to detach the sensor body from the corresponding connector, and to solve the problem simply by exchanging the sensor body. More specifically, re-connection of electric cords and a control equipment such as the PLC and associated works of binding of the lines when the sensor body is exchanged in the conventional system, can be avoided.

[0040] Further, if it is made possible to draw out the sensor body from the connector while maintaining coupling of adjacent connectors with each other, even when the aligned arrangement of the sensor bodies in the system is disconnected because of a failure of any sensor body, for example, power feed to the sensor bodies succeeding the defective portion is continued.

[0041] The connector system of the present inven-

tion is also applicable for power connection between sensors of the same type but of different specifications, as in the case of photoelectric sensors in accordance with different specifications, as well as to power connections of sensors of different types, as in the case of a photoelectric sensor and a proximity sensor. In such a case, what is necessary in designing the sensor body is simply to consider the position of the connector, so as to enable connection between neighboring connectors with each other.

[0042] When the connector system of the present invention is applied, limitations in the design of the sensor body as expected when the structure for electrical connection with an adjacent sensor body is to be provided on the sensor body itself, can be eliminated.

[0043] The sensor body designed corresponding to the connector system of the present invention may be used connected to the main connector and not electrically connected to other sensors. In such a case, the sensor may be used as a sensor having similar function and appearance to the conventional sensor to which the electric cord is detachably attached.

[0044] The sensor body designed corresponding to the connector system of the present invention may be used connected to the connector of the conventional structure not having the connecting structure with the neighboring connector. In this case, the electrical connecting structure to the neighboring sensor unnecessary in such use, is absent.

[0045] As described above, as the electrical connecting structure is provided in the connector, the user of the sensor can flexibly select an optimal system dependent on the intended use, using the sensor body standardized to be used with the connector system of the present invention.

[0046] In a preferred embodiment of the present invention, in addition to the power feed line, one or two or more signal lines are included in the electric cord introduced to the main connector, and corresponding number of signal terminals are provided at the joint for the sensor body of the main connector. Further, the main connector includes therein an internal conductor connecting respective ones of the signal lines of the electric cord to the corresponding signal terminals on the side of the joint for the sensor body, respectively.

[0047] Further, an electric cord including one or two or more signal lines is introduced to the sub connector, and the corresponding number of signal terminals are provided at the joint for the sensor body of the sub connector. Further, the sub connector includes therein an internal conductor coupling the signal lines of the electric cord with the corresponding signal terminals at the side of the junction for the sensor bodies, respectively.

[0048] Therefore, each connector provides, in addition to the power feed function for the sensor body, the function of connecting the signal terminals in the sensor body with the signal terminals in the electric cord.

[0049] More specifically, it becomes possible to

feed power to the sensor body and to transmit/receive a signal between the sensor body and a control device such as a PLC, through the connector.

[0050] Further, in this case also, the connector and a sensor body is detachably coupled. Therefore, when there is a trouble in the sensor body, it is possible to detach the corresponding sensor body from the corresponding connector, and to exchange the sensor body only, and the trouble is eliminated. More specifically, reconnection between the electric cords and a control device and the like and associated binding when the sensor body is exchanged in the conventional system, can be avoided.

[0051] Further, in a sensor system in which exchange of signals between adjacent sensor bodies is possible, drawing out the electric cord for signal output from each sensor becomes unnecessary. In that case, the sub connector will be simply a connector used for power feed only.

[0052] As described above, according to the present invention, the power feed line is unnecessary for the connectors other than the main connector. Therefore, the number of power feed lines can significantly be reduced for the overall system. Further, as the sensor bodies of common structure same for the main and sub sensors are employed, the cost can be reduced and the inventory management is made easier. Further, if a failure occurs in any of the sensor bodies, it is possible to simply exchange the defective sensor body only, while maintaining the electric cords used up to that time point.

[0053] Further, according to the present invention, when a plurality of sensor bodies are arranged in a row and in contact with each other, the number of sensors to be arranged can be flexibly changed, and the minimum number of power feed lines can be maintained regardless of the number of sensors to be arranged.

[0054] The foregoing and other objects, features, aspects and advantages of the present invention will become more apparent from the following detailed description of the present invention when taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0055]

Fig. 1 is a perspective view showing an appearance of the overall sensor system in accordance with an embodiment of the present invention.

Fig. 2A is a side view of the sensor body to which a sub connector of the sensor system shown in Fig. 1 is connected, and Fig. 2B shows a side view of the sensor body to which a main connector is connected.

Fig. 3 is a perspective view showing the connectors of the sensor system shown in Fig. 1 separated from the sensor bodies.

Fig. 4A is a side view of the sensor body with the sub connector separated, corresponding to Fig. 2A, and Fig. 4B is a side view showing the sensor body with the main connector separated, corresponding to Fig. 2B.

Figs. 5A and 5B are perspective views of the appearance of the sub connector of the sensor system shown in Fig. 1, viewed from two different directions.

Fig. 6 shows the sub connector of Figs. 5A and 5B viewed from the side of the sensor body.

Fig. 7 is an exploded perspective view of the sub connector shown in Figs. 5A and 5B viewed from behind one side.

Fig. 8 is an exploded perspective view of the sub connector shown in Figs. 5A and 5B viewed from behind the opposing side from Fig. 7.

Figs. 9A and 9B are enlarged perspective views showing the appearance of the distributor used for the sub connector of the sensor system shown in Fig. 1, viewed from two different directions.

Figs. 10A and 10B are perspective views showing the appearance of the main connector of the sensor system shown in Fig. 1, viewed from two different directions.

Fig. 11 shows the main connector of Figs. 10A and 10B viewed from the side of the sensor body.

Fig. 12 is an exploded perspective view of the main connector shown in Figs. 10A and 10B.

Figs. 13A and 13B are enlarged perspective views of the appearance of the distributor used for the main connector of the sensor system shown in Fig. 1, viewed from two different directions.

Fig. 14 is a circuit diagram schematically showing the feeding and receiving of power to the sensor bodies and transmission and reception of signals from the sensor bodies to the signal lines, when the sensor bodies and main and sub connectors are coupled in the sensor system shown in Fig. 1.

Fig. 15 is an illustration representing the function of the sensor system shown in Fig. 1.

Fig. 16 is a perspective view showing another example of the row of connectors of the sensor system in accordance with the present invention.

Fig. 17 is a perspective view schematically showing the overall conventional sensor system.

Fig. 18 is an illustration representing the method of power feeding in the conventional sensor system.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0056] Embodiments of the sensor system in accordance with the present invention and the connectors used therefor will be described in detail with reference to the appended drawings.

[0057] Fig. 1 is a perspective view showing the overall appearance of the sensor system in accordance

with the present invention, Fig. 2 includes side views of the sensor body and the connector when coupled, Fig. 3 is a perspective view showing the appearance of the sensor bodies separated from the connectors, and Fig. 4 includes side views of the sensor body and the connector separated from each other.

[0058] As can be seen from Fig. 1, the sensor system in accordance with the present embodiment is implemented as a sensor system including a plurality of fiber type photoelectric sensors.

[0059] The sensor system includes a plurality of sensor bodies 1 (1b, 1a, to 1an) arranged aligned and in contact with each other, and a plurality of connectors (one main connector 3 and a plurality of sub connectors 2₁ to 2n) that are detachably coupled to the sensor bodies 1 and detachably coupled to neighboring connectors with each other.

[0060] Sensor bodies 1 are arranged in tight contact with each other on a DIN rail 4, in this example. To that sensor body 1b which is arranged at an end portion of the system (left end of the figure when viewed from the front), a main connector 3 is connected. A plurality of sensor bodies 1a₁ to 1an arranged aligned and in contact with each other to form a row following the right side of the sensor body 1b are connected to sub connectors 2₁ to 2n.

[0061] Fig. 2A shows the sensor body 1a connected with sub connector 2, and Fig. 2B shows the sensor body 1b connected with main connector 3. As is apparent from these figures, in the present embodiment, the sensor bodies 1a and 1b to which the sub connector 2 and the main connector 3 are connected are of the same specification. More specifically, different from the conventional sensor system having the line saving structure, it is unnecessary to prepare the sensor bodies of two different structures as the main sensor fed from an electric cord and a sub sensor fed from the neighboring sensor.

[0062] In this example, the sensor body 1 has a flat, approximately rectangular sensor case 10. On opposing side surfaces of sensor case 10, a pair of light emitting and receiving windows 11a and 11b for optical communication are provided. Between neighboring sensors, infrared ray is emitted/received through the emitting and receiving windows 11a and 11b, enabling various settings and adjustment of the photoelectric sensors.

[0063] In sensor case 10, a control panel, not shown, is attached. On the control panel, various circuits such as a power supply circuit, a measurement control circuit, and a communication circuit within neighboring units, light emitting elements and light receiving elements for optical communication between neighboring sensors and so on are mounted. Further, there is a rail receiving portion 12 at the bottom surface of sensor case 10, for mounting sensor body 1 on the DIN rail 4.

[0064] From a front surface 10a of sensor case 10, optical fibers 5a and 5b are drawn out, and tip ends of

optical fibers 5a and 5b form sensor head portions 6a and 6b as shown in Fig. 1. The photoelectric sensor detects presence/absence and states and the like of an object 7, by emitting and receiving a red light beam through the sensor head portions 6a and 6b.

[0065] On a rear surface 10b of sensor case 10, main connector 3 or sub connector 2 is connected. Further, an electric cord 9 is drawn out from main connector 3, and an electric cord 8 is drawn out from sub connector 2, respectively.

[0066] Fig. 3 and the side views of Figs. 4A and 4B show the sensor bodies 1 (1a, 1b) and connectors 2, 3 separated from each other. Fig. 4A shows sensor body 1a separated from sub connector 2, and Fig. 4B shows sensor body 1b separated from main connector 3, respectively.

[0067] As shown in Figs. 3 and 4A and 4B, a joint 13 for the connector is formed on the rear surface 10b of sensor body 1 (1a, 1b). By means of the joint 13 for the connector and a joint (shown by the reference character 24 in Fig. 6) for the sensor body of the connector not shown in these figures, the sensor body 1 and each of the connectors 2 and 3 are detachably coupled.

[0068] On the upper surfaces of connectors 2 and 3, elastic projection pieces 204 and 304 having a stepped portion are provided, respectively. At a ceiling surface, not shown, of the joint 13 for connector of sensor body 1, an engaging piece for engaging with the elastic projection pieces 204, 304 at the stepped portion is provided. This prevents disengagement of the connectors 2, 3 with the sensor body 1, when the connector and the sensor body are connected.

[0069] At the joint 13 for the connector, four terminal pins 14a to 14d protrude from the inside of sensor case 10 toward the direction of connection between the sensor body 1 and a connector (along the lengthwise direction). These four terminal pins 14a to 14d are arranged at a prescribed pitch interval in the up/down direction, and used as a control output terminal pin (signal terminal pin) 14a, a power receiving terminal pin 14b, an analog output terminal pin (signal terminal pin) 14c and a power receiving terminal (ground side) pin 14d, in this order from the uppermost one. The terminal pins 14 are electrically connected to a circuit board, not shown, forming an internal electric circuit within the sensor case, and therefore, power feed from connector 2 or 3 to sensor body 1 and signal output from the sensor body 1 to the connector are possible through the terminal pins 14a to 14d.

[0070] The structure of sub connector 2 will be described in detail with reference to Figs. 5 to 9.

[0071] As shown in Figs. 5 to 8, sub connector 2 has a connector housing 20 formed of an insulating body. As shown in Figs. 7 and 8, respectively, connector housing 20 is formed divided into two pieces, that is, a front connector housing 20a having the joint for the sensor body (represented by reference character 24 in Fig. 6) and a rear connector housing 20b having an inlet for

introducing the electric cord.

[0072] A pair of claw-shaped projection pieces 201a and 201b extending horizontally toward the front connector housing 20a protrude from upper and lower end portions of rear connector housing 20b. The claw-shaped projection pieces 201a and 201b are engaged with engaging projections 20a and 20b provided at upper and lower end portions of the front connector housing 20a, whereby disengagement or slipping of the connector housings 20a and 20b, when the housings are coupled, is prevented.

[0073] On the back surface of rear connector housing 20b, an electric cord inlet 203 is provided, and from an edge of electric cord inlet 203, a pair of claw-shaped projection pieces 203a and 203b for fixing a stopper ring 21 from the inside are provided protruded rearward. Here, stopper ring 21 is provided for preventing slipping of electric cord 8 out from the connector housing 20. The stopper ring 21 is attached after the electric cord 8 is inserted to electric cord inlet 203 of rear connector housing 20b, by engaging the claw-shaped projection pieces 203a and 203b with the stepped portions 210a and 210b provided on stopper ring 21. Accordingly, the electric cord 8 is pinched from above and from below by claw-shaped projection pieces 203a and 203b, whereby slipping out of electric cord 8 is prevented.

[0074] As can be seen from the perspective view of Fig. 5A, front view of Fig. 6 and the exploded perspective view of Fig. 8, there is provided a joint 22 for a neighboring connector for power reception, having a power receiving terminal (power receiving terminal portions 253b, 253d of internal conductor pieces 25b and 25d for power feeding) for receiving power from the neighboring connector. The power receiving terminals (power receiving terminal portions 253b and 253d of internal conductor pieces 25b and 25d for power feed) will be described in detail later.

[0075] Joint 22 for the neighboring connector for power reception has, in addition to the power receiving terminal (power receiving terminal portions 253b, 253d), a clip piece 221 and a columnar insertion piece 222. Clip piece 221 includes a pair of elastic pieces each having a projection at the tip end provided parallel to each other in the up/down direction. The insertion piece 222 is a columnar projection for preventing rattling when neighboring connectors are coupled to each other, and it is provided below clip piece 221.

[0076] As shown in the perspective view of Fig. 5B, front view of Fig. 6 and exploded perspective view of Fig. 7, on the right side surface (the side surface which will be father from the main connector 3) of rear connector housing 20b, there is provided a joint 23 for the neighboring connector for power feed, including a power feed terminal (power feed terminal portions 254b and 254d for the neighboring connectors of internal conductor pieces 25b and 25d for power feed) for feeding and receiving power to and from the neighboring connectors. The power feed terminal (internal conduc-

tor pieces 25b and 25d for power feed and power feed terminal portions 254b and 254d) will be described in detail later.

[0077] At the joint 23 for the neighboring connector for power feed, there is provided, in addition to the power feed terminal (power feed terminal portions 254b, 254d of internal conductor pieces 25b, 25d for power feed), an engaging hole 231 to be engaged with clip piece 221 and a slot 232 to which the columnar insertion piece 222 is inserted, arranged along the up/down direction. The engaging hole 231 has stepped portions 231a and 231b to receive and engage with the projections at the tip ends of clip piece 221, as shown in Fig. 6.

[0078] Neighboring connectors are electrically and mechanically connected with each other by means of the joint 22 for the neighboring connector for power reception of one connector and the joint 23 for the neighboring connector for power feed of the other connector. More specifically, the insertion piece 222 of one connector is inserted to the slot 232 of the other connector, and at the same time, the clip piece 221 of the one connector is inserted to the engaging hole 231 of the other connector, for coupling with each other. At this time, as the clip piece 221 is engaged with the engaging hole 231, the coupling between the connectors is secured.

[0079] More specifically, clip piece 221 and insertion piece 222 are the projections as mechanical structures for connection with the neighboring connector, and power reception terminal portions 253b and 253d are projections as electric structures for connection with the neighboring connector. Further, the engaging hole 231 and a slot 232 are the recessed portions as the mechanical structures for connection with the neighboring connector, and slots 233 and 234 having power feed terminal portions 254b and 254d therein, which will be described later, are recessed portions as electrical structures for connection with the neighboring connector.

[0080] As shown in Fig. 6, on a front surface of sub connector 2 (on the side of the sensor body), there is a joint 24 for the sensor body. The joint 24 for the sensor body has four slots 241a to 241d to which the four terminal pins 14a to 14d of sensor body 1 can be inserted.

[0081] Inside the slots 241a to 241d, there are arranged power feed terminals (power feed terminal portions 251b and 251d for the sensor body of internal conductor for power feed) for feeding power from sub connector 2 to sensor body 1, and signal terminals (signal terminal portions 251a, 251c of internal conductor pieces 25a and 25c for the signals) for receiving signal data passed from the sensor body 1. The signal terminals (signal terminal portions 251a, 251c of internal conductor pieces 25a and 25c for the signals) will be described in detail later.

[0082] When sensor body 1 and sub connector 2 are connected, four terminal pins 14a to 14d of sensor body 1 are inserted to corresponding slots 241a to

241d, respectively, enabling feeding of power from the sub connector 2 to the sensor body 1 and signal transmission from sensor body 1 to sub connector 2.

[0083] As shown in Figs. 7 and 8, connector housing 20 accommodates a distributor 25 having independent four conductor pieces 25a to 25d.

[0084] At a joining surfaces of front connector housing 20a and rear connector housing 20b, accommodating recessed portions are provided, allowing mounting of these four conductor pieces 25a to 25d not in contact with each other. As the conductor pieces 25a to 25d are fitted in the accommodating recessed portions, the conductor pieces are positioned and fixed at appropriate intervals, within the connector housing 20.

[0085] As is apparent from the enlarged perspective view of Fig. 9, conductor pieces 25a to 25d have terminal portions (signal terminal portions 251a, 251c and power feed terminal portions 251b and 251d for the sensor body) electrically connected to and corresponding to terminal pins 14a to 14d protruded from the sensor body 1, respectively. The terminal portions 251a to 251d are made resilient to ensure secure contact with the terminal pins 14a to 14d of sensor body 1 within the slots 241a to 241d. The terminal portions 251 are arranged at prescribed positions inside the slots 241a to 241d.

[0086] The conductor pieces 25a to 25d have terminal portions 252a to 252d for line connection, for connecting various electric lines to the conductor 25 by fixing means such as the solder. The uppermost conductor piece 25a and third conductor piece 25c from the top are signal conductor pieces for electrically connecting the signal lines 8a and 8b contained in electric cord 8 to signal terminal pins 14a and 14c of sensor body 1, respectively.

[0087] Signal line 8a is connected to the electrical connection terminal portion 252a of signal conductor piece 25a, and signal line 8b is connected to line connection terminal portion 252c of signal conductor piece 25c, respectively.

[0088] The signal terminal pins 14a and 14c of sensor body 1 are inserted to terminal pin slots 241a and 241c shown in Fig. 6. At this time, signal terminal portion 251a of signal conductor piece 25a and signal terminal portion 251c of signal conductor piece 25c are brought into resilient contact with signal terminal pins 14a and 14c to raise the pins from below, respectively, whereby the signal terminal pins 14a and 14c of the sensor body 1 are brought into contact with the signal terminal portions 251a and 251c of sub connector 2.

[0089] More specifically, when sensor body 1 and sub connector 2 are connected, signal lines 8a and 8b contained in electric cord 8 are electrically connected to signal terminal pins 14a and 14c of the sensor body 1 through signal conductor pieces 251a and 251c of sub connector 2, respectively.

[0090] The second conductor piece 25b from the top and the lowermost (fourth) conductor piece 25d are power internal conductor pieces, for feeding the power

received from the neighboring connector on the left side (closer to the main connector in the present embodiment) to the neighboring connector on the right side, and to feed the power to the sensor body 1.

[0091] Power conductor pieces 25b and 25d have power receiving terminal portions 253b and 253d for receiving power from a neighboring connector on one side. As shown in Fig. 5A, receiving terminal portions 253b and 253d are arranged with tip portions protruded outward from connector housing 20 toward the neighboring connector, through slot 223 provided between clip piece 221 and inserting piece 222 and through the slot 224 provided below inserting piece 222, of the joint 22 for the neighboring connector for power reception, respectively.

[0092] Further, power conductor pieces 25b and 25d have power feed terminal portions 254b and 254d for the neighboring connector, for feeding power to the neighboring connector on the other side. Power feed terminal portions 254b and 254d are made resilient so as to establish pressure contact with power receiving terminal portions 253b and 253d of the neighboring connector from above, when connected to the neighboring connector. As shown in Fig. 5B, power feed terminal portions 254b and 254d are placed in a slot 233 provided within engaging hole 231 and slot 232 and in slot 234 provided below slot 232, of the joint 23 for the neighboring connector for power feed, respectively. The line connecting terminal portions 252b and 252d of conductor pieces 25b and 25d are not used in the present embodiment.

[0093] With such a structure, when connected to the neighboring connector on the left side (closer to the main connector), the power receiving terminal portions 253b and 253d of sub connector 2 are in pressure contact from above with the power feed terminal portions 254b and 254d of the neighboring connector in slots 233 and 234 of the neighboring connector, and thus electrically connected with each other.

[0094] In the similar manner, when coupled to the neighboring connector on the right side (farther from the main connector), the power feed terminal portions 254b and 254d press the power receiving terminal portions 253b and 253d of the neighboring connector to be in contact with and electrically connected to each other.

[0095] When sensor body 1 is coupled to sub connector 2, power receiving terminal pins 14b and 14d of sensor body 1 are inserted to terminal pin slots 241b and 241d shown in Fig. 6, respectively. At this time, the resilient terminal portion 251b of power conductor piece 25b presses terminal pin 14b and resilient terminal portion 251d of conductor piece 25d presses terminal pin 14d, respectively from below, and are electrically connected to each other.

[0096] More specifically, the power feed terminal portions 254b and 254d of the neighboring connector on the left side, the power receiving terminal pins 14b and 14d of sensor body 1, and power receiving terminal

portions 251b and 251d of the neighboring connector on the right side are electrically connected with each other, respectively.

[0097] Referring to Fig. 1, for the sub connector 2n arranged on the right end of the sensor system when viewed from the front side of this figure, there is no neighboring sub connector on the right side. Here, the power is passed from sub connector 2n only to the sensor body 1.

[0098] The structure of main connector 3 will be described with reference to Figs. 10 to 13. Fig. 10 includes perspective views showing the appearance of the main connector, Fig. 11 is a front view of the main connector, Fig. 12 is an exploded perspective view of the main connector, and Fig. 13 shows, in enlargement, a distributor used for the main connector. Fig. 10A shows one side surface of the main connector provided with the joint for the neighboring connector for power feed, and Fig. 10B shows the other side surface of the main connector.

[0099] Main connector 3 is in many respects, similar to sub connector 2. Therefore, portions having the same structure as those of sub connector 2 will be represented by the reference characters common in the lower one digit (when the reference character consists of two digits) or lower two digits (when the reference character consists of three digits) to those used in the description of the sub connector 2, and detailed descriptions will not be repeated.

[0100] As shown in Figs. 10A, 10B and 12, an electric cord 9 which is inserted to the rear connector housing 30b of the main connector includes, in addition to signal lines 8a and 8b, power feed lines 9a and 9b.

[0101] As can be seen from Fig. 10A, on one side of front connector housing 30a, there is provided a joint 33 for the neighboring connector for power feed, as in the sub connector 2. More specifically, engaging hole 331 and a slot 332 for receiving the clip piece 221 and the inserting piece 222 of the neighboring sub connector 2 are provided along the up/down direction, and between the engaging hole 331 and slot 332, there is a slot 333 to which the power receiving terminal portion 253b of the neighboring sub connector 2 is inserted, and below the slot 332, there is the slot 334 to which the power receiving terminal portion 253d is inserted. More specifically, the engaging hole 331 and slot 332 form recessed portions as mechanical structure for connection with the neighboring connector, and slots 333 and 334 having the power feed terminals provided therein form recessed portions as electrical structure for connection with the neighboring connector.

[0102] By contrast, referring to Fig. 10B, there is no joint for the neighboring connector on the other side surface of the front connector housing 30a. This is because the main connector 3 is coupled to the sensor body 1b that is arranged on the left end of the sensor system, as shown in Fig. 1.

[0103] More specifically, power is received by the

main connector not form the neighboring connector but from the power feed lines 9a and 9b contained in electric cord 9. Therefore, as shown in Figs. 13A and 13B, internal conductor pieces 35b and 35d for power feed of a distributor 35 used in main connector 3 are not provided with the power receiving terminals (corresponding to the power receiving terminal portions 253b and 253d of the sub connector) for receiving the power from the neighboring connector. In place thereof, power feed lines 9a and 9b are connected to line connection terminal portions 352b and 352d of power receiving conductor pieces 35b and 35d, and the power is passed from power feed lines 9a and 9b to power feed conductor pieces 35b and 35d. Therefore, the power feed terminal portion is not exposed on that side of the main connector on which the neighboring connector does not exist (the side which will be the left side surface of the sensor system in Fig. 1), and therefore the risk of electrical short-circuit or receiving electrical shock by accidentally touching the power feed terminal portion can be avoided.

[0104] The mechanical and electrical connecting structures for the neighboring connector provided on one side (closer to the main connector) of the sub connector have projected shapes, and the mechanical and electrical connecting structure with the neighboring connector provided on the other side (farther from the main connector) of the sub connector have recessed shapes to receive the protrusions. Further, the mechanical and electrical connecting structures provided only on the right side of the main connector also have the recessed shapes. Therefore, in the row of connectors formed by mutually connecting these connectors, the connecting structure of the sub connector positioned on the right end (represented by 2n in Fig. 1) does not have the protruded portion on the side where the neighboring connector does not exist.

[0105] More specifically, there is no projection on either side of the row of connectors. Therefore, the row of sensors to which the connectors are connected can be placed in tight contact with other devices aligned on the DIN rail.

[0106] If there is a projection protruding from an end of the row of sensors, it is possible that an operator's clothes may be accidentally caught on the projection, or something may possibly hit the protrusion. The present embodiment eliminates such a possibility. The joint for the neighboring connector on the side, on which the neighboring connector does not exist, of the sub connector arranged at the distal end of the row of sensors may be covered by applying a sticker, for example, so that the connecting structure is concealed. This may further enhance electrical safety.

[0107] When main connector 3 and sensor body 1 are coupled, power receiving terminal pins 14b and 14d of sensor body 1 are inserted to slots 341b and 341d for the power receiving terminal pins shown in Fig. 11, respectively. At this time, power feed terminal portion

351b for the sensor body of power internal conductor piece 35b presses power receiving terminal pin 14b from below, the power feed terminal portion 351d for the sensor body of power conductor piece 35d presses power receiving terminal pin 14d from below, and these are electrically connected to each other.

[0108] When main connector 3 and a neighboring sub connector 2 are coupled, power feed terminal portion 354b for the neighboring connector of power conductor piece 35b presses power receiving terminal portion 253b of the neighboring connector 2 from above, and power feed terminal portion 354d for the neighboring connector presses the power receiving terminal portion 253d of the neighboring connector from above, and these are electrically connected to each other.

[0109] More specifically, when main connector 3 and sensor body 1 are coupled, power lines 9a and 9b connected to main connector 3 are electrically connected to power receiving terminal pins 14b and 14d of the sensor body through power conductor pieces 35b and 35d of main connector 3, and when main connector 3 and the neighboring sub connector 2 are coupled, the power lines 9a and 9b are electrically connected to power receiving terminal portions 253b and 253d of the neighboring sub connector 2, through power conductor pieces 35b and 35d of main connector 3.

[0110] By the above described structure, the present embodiment enables connection of one main connector 3 and a plurality of sub connectors 2₁ to 2_n with the corresponding sensor bodies 1 (1b, 1a₁ to 1a_n), and in addition, enables feeding of power supplied to the main connector 3 to each sensor body 1, by forming a row of connectors by coupling the connectors with each other.

[0111] Fig. 14 schematically shows the manner how the power is fed to the sensor body through the row of connectors and how the signals are passed from the sensor bodies to the signal lines 8a and 8b through the connectors in accordance with the present embodiment. For convenience, only the main connector 3 and sub connectors 2₁ and 2₂ are shown as connectors, and only the sensor bodies 1b and 1a₁ and 1a₂ connected to these connectors are shown as the sensor bodies 1.

[0112] As can be seen from the figure, a control output and an analog output transmitted from the sensor body 1 (1b, 1a₁, 1a₂) to which the main connector 3 or the sub connector 2 (2₁, 2₂) is connected are passed through internal conductor piece 35a, 35c, 25a or 25c for the signals of each connector and signal terminal pins 14a, 14c to signal lines 8a, 8b. Accordingly, signal transmission from the sensor body 1 (1b, 1a₁, 1a₂) to a control device such as a PLC, becomes possible.

[0113] The power introduced from power lines 9a and 9b of main connector 3 is passed to power receiving terminal pins 14b and 14d of sensor body 1b to which main connector 3 is connected, through power internal conductor pieces 35b and 35d of main connector

tor 3. Thus, the power is supplied to the circuit board in sensor body 1b.

[0114] At the same time, the power introduced from power lines 9a and 9b of main connector 3 is passed through power conductor pieces 35b and 35d of main connector 3 to power receiving terminal portions 253b and 253d of the neighboring sub connector 2₁. Further, the power received by the power receiving terminal portions 253b and 253d of the neighboring connector 2₁ is passed through power internal conductor pieces 25b and 25d to power receiving terminal pins 14b and 14d of sensor body 1a₁. Thus, the power introduced from electric cord 9 (power lines 9a, 9b) to main connector 3 is supplied to the circuit board in sensor body 1a₁.

[0115] Further, the power received at power receiving terminal portions 253b and 253d of sub connector 2₁ is passed through the power internal conductor pieces 25b and 25d of sub connector 2₁ to power receiving terminal portions 253b and 253d of the neighboring sub connector 2₂. The power received by the power receiving terminal portions 253b and 253d of the neighboring sub connector 2₂ is passed through power internal conductor pieces 25b and 25d of the sub connector 2₂ to power receiving terminal pins 14b and 14d of sensor body 1a₂. Accordingly, the power introduced to main connector 3 is supplied to the circuit board of sensor body 1a₂.

[0116] In this manner, in the sensor system in accordance with the present embodiment, the power introduced to the main connector 3 is successively passed to the plurality of sub connectors 2 (2₁ ~ 2_n) arranged in contact with each other to form a row following main connector 3, and further supplied to the circuit boards of the sensor bodies 1 (1b, 1a₁ to 1a_n) to which the connectors 2 and 3 are connected. More specifically, by the connector system consisting of the main connector 3 and a plurality of sub connectors 2, a power supply line is implemented.

[0117] The structure of the sensor system in accordance with the embodiment described above can be schematically represented as Fig. 15. More specifically, the power supplied to main connector 3 is supplied through the row of connectors consisting of the main connector 3 and the plurality of sub connectors 2₁ to 2_n to the circuit boards in the sensor bodies 1 (1b, 1a₁ to 1a_n) to which respective connectors are connected, and therefore it becomes unnecessary to connect a power feed line (power feed lines 9a, 9b of electric cord 9) to each sensor. Thus, the number of power feed lines for the overall system can significantly be reduced.

[0118] In addition, power feed through the electric cord 9 is effected through main connector 3. Therefore, sensor bodies having the common structure can be used as the sensor bodies 1, regardless of whether the main connector or the sub connector is to be connected thereto. Therefore, as compared with the conventional sensor system in which the power is fed and received between the sensor bodies, the number of parts and

steps of managing the parts can be reduced, resulting in reduced cost. Further, there is no distinction between the main and sub sensors, inventory management of the sensor bodies themselves is facilitated.

[0119] Each connector 2, 3 is detachably coupled to sensor body 1. Therefore, when a sensor body falls as schematically shown by the reference character 1a₃ in the figure, it is possible to simply exchange the failed sensor body 1a₃, while maintaining the electric cord 8₃ which has been connected to connector 2₃.

[0120] Further, if it is made possible to draw out the sensor body from the connector while maintaining coupling between neighboring connectors, then, it becomes possible, even when a sensor body is absent in the middle of the row of sensors, for example to exchange the sensor body as schematically represented by the reference character A in the figure, to maintain power supply to the sensor bodies 1a₆ to 1a_n following the absent portion.

[0121] Further, as the neighboring connectors can be detachably coupled to each other, it becomes possible to increase/decrease the number of sensors to be arranged.

[0122] Though detailed description is not given as it is not directly related to the present invention, it is possible by the sensor system in accordance with the present embodiment to perform optical communication between the sensor bodies through light emitting/receiving windows 11a and 11b shown in Figs. 1 to 4B. Therefore, in the present embodiment, by relaying a control output and analog output transmitted from each sensor body 1 to the neighboring sensor bodies one by one for transmission/reception, signal transmission from a dedicated communication unit arranged at an end of the row of sensors to the control device such as the PLC through a serial communication in collective manner is possible. By this configuration, it becomes unnecessary to draw out an electric cord 8 (signal lines 8a, 8b) from each sensor, and therefore, the number of lines of the overall sensor system can further be reduced.

[0123] Fig. 16 shows an example of the row of connectors having such a configuration. As shown in this figure, an electric cord 9 is drawn out from the main connector 3 positioned at the left end of the row of connectors. From the plurality of sub connectors 2, however, there is not any electric cord drawn out. More specifically, the sub connectors 2 are each used as a simple power feeding connector.

[0124] Although the present invention has been described and illustrated in detail, it is clearly understood that the same is by way of illustration and example only and is not to be taken by way of limitation, the spirit and scope of the present invention being limited only by the terms of the appended claims.

Claims

1. A sensor system, comprising:

a plurality of sensor bodies (1) arranged aligned and in contact with each other, and a plurality of connectors (2, 3) which can be detachably coupled to the sensor bodies respectively and to neighboring ones of the connectors with each other; wherein

said plurality of connectors include at least one main connector (3) and one or two or more sub connectors (2);

each of said sensor body is provided with a joint (13) corresponding to a connector including a power receiving terminal (14b) for receiving, from the connector, a power to an internal electric circuit;

said main connector includes

a joint (34) for a sensor body including a power feed terminal for feeding power to an internal electric circuit of said sensor body,

a joint (33) for a neighboring connector including a power feed terminal for feeding power to a neighboring connector,

an electric cord inlet (303) for drawing in an electric cord (9) including a power feed line into said connector, and

an internal conductor (35a, 35b, 35c, 35d) for conducting the power fed through said electric cord to the power feed terminal included in said joint for the sensor body and to the power feed terminal included in said joint for the neighboring connector, inside the main connector;

said sub connector includes

a joint (24) for a sensor body, including a power feed terminal for feeding power to the internal electric circuit of said sensor body,

a joint (22) for a first neighboring connector, including a power receiving terminal for receiving power from one neighboring connector,

a joint (23) for a second neighboring connector, including a power feed terminal for feeding power to the other neighboring connector, and

an internal conductor (25a, 25b, 25c, 25d) for conducting the power received through the power receiving terminal included in said joint for the first neighboring connector, to the power feed terminal included in said joint for the sensor body and to the power feed terminal included in said joint for the second neighboring connector, inside the sub connector; and

by coupling an arbitrary number of said sub connectors adjacent to said main connector, power fed to said main connector through said electric cord is distributed to each of said sensor bodies through a row of the connectors.

2. The sensor system according to claim 1, wherein said joint (33) for the neighboring connector of said main connector (3) is provided only on one side surface and, and no joint exist on the other side surface.

face.

3. The sensor system according to claim 1, wherein a connecting structure for establishing mechanical and electrical connections with a neighboring connector is provided at said joint (33) for the neighboring connector of said main connector (3), said joint (22) for the first neighboring connector and said joint (23) for the second neighboring connector of said sub connector;

the connecting structure of said joint for the first neighboring connector of said sub connector has a projecting portion protruding toward a connector neighboring said joint corresponding to the first neighboring connector; and the connecting structure of said joint for the neighboring connector of said main connector and the connecting structure of said joint for the second neighboring connector of said sub connector each have a recessed portion receiving the projecting portion of the connector neighboring the joint, and is free of any projecting portion protruding toward a neighboring connector.

4. The sensor system according to claim 1, wherein said sensor body (1) is a sensor body of a head separation type sensor including a fiber type photoelectric sensor, an ultrasonic sensor and a proximity sensor.
5. A connector system including a plurality of connectors (2, 3) that can be detachably coupled to neighboring ones in an aligned row, and each can be detachably coupled to a sensor body (1) along a longitudinal direction, wherein

said plurality of connectors include at least one main connector (3) and one or two or more sub connectors (2);

said main connector includes

a joint (34) for a sensor body including a power feed terminal for feeding power to an internal electric circuit of said sensor body,

a joint (33) for a neighboring connector including a power feed terminal for feeding power to a neighboring connector,

an electric cord inlet (303) for drawing in an electric cord (9) including a power feed line into said connector, and

an internal conductor (35a, 35b, 35c, 35d) for conducting the power fed through said electric cord to the power feed terminal included in said joint for the sensor body and to the power feed terminal included in said joint for the neighboring connector, inside the main connector;

said sub connector includes

a joint (24) for a sensor body, including a power feed terminal for feeding power to the internal electric circuit of said sensor body,

a joint (22) for a first neighboring connector, including a power receiving terminal for receiving power from one neighboring connector, a joint (23) for a second neighboring connector, including a power feed terminal for feeding power to the other neighboring connector, and an internal conductor (25a, 25b, 25c, 25d) for conducting the power received through the power receiving terminal included in said joint for the first neighboring connector, to the power feed terminal included in said joint for the sensor body and to the power feed terminal included in said joint for the second neighboring connector, inside the sub connector; and by coupling an arbitrary number of said sub connectors adjacent to said main connector, the power supplied to said main connector through said electric cord is distributed to said joint for the sensor body of each of said main and sub connectors.

6. The connector system according to claim 5, wherein

said electric cord (9) introduced to said main connector (3) includes, in addition to the power feed line, one or two or more signal lines, said joint (34) for the sensor body of said main connector includes a corresponding number of signal terminals, and an internal conductor coupling respective ones of the signal lines of said electric cord to the corresponding signal terminals of said joint for the sensor body is provided in said main connector; and wherein said electric cord (8) including at least one signal line is introduced to said sub connector (2), said joint (24) for the sensor body of said sub connector includes a corresponding number of signal terminals, and an internal conductor (25a, 25c) coupling respective ones of the signal lines of said electric cord to the corresponding signal terminals of the joint of said sensor body is provided in said sub connector.

7. The connector system according to claim 5, wherein

said joint (33) for the neighboring connector of said main connector (3) is provided only on one side surface and, and no joint exist on the other side surface.

8. The connector system according to claim 5, wherein

a connecting structure for establishing mechanical and electrical connections with a neighboring connector is provided at said joint (33) for the neighboring connector of said main connector (3), said joint (22) for the first neighboring connector and said joint (23) for the second neighboring connector of said sub connector;

the connecting structure of said joint for the first neighboring connector of said sub connector has a projecting portion protruding toward a connector neighboring said joint for the first neighboring connector; and

the connecting structure of said joint for the neighboring connector of said main connector and the connecting structure of said joint for the second neighboring connector of said sub connector each have a recessed portion receiving the projecting portion of the connector neighboring the joint, and is free of any projecting portion protruding toward a neighboring connector.

9. The connector system according to claim 5, wherein

said sensor body (1) is a sensor body of a head separation type sensor including a fiber type photoelectric sensor, an ultrasonic sensor and a proximity sensor.

10. A main connector, having a connector body (3) that can be detachably coupled to one of a plurality of sensor bodies (1) arranged aligned and in contact with each other, said connector body including

a joint (34) for a sensor body including a power feed terminal for feeding power to an internal electric circuit of said sensor body, a joint for a neighboring connector including a power feed terminal for feeding power to a neighboring connector, an electric cord inlet (303) for drawing in an electric cord including a power feed line into said connector, and an internal conductor (35a, 35b, 35c, 35d) for conducting the power fed through said electric cord to the power feed terminal included in said joint for the sensor body and to the power feed terminal included in said joint for the neighboring connector, inside the main connector.

11. The main connector according to claim 10, wherein

said electric cord (9) introduced to said main connector (3) includes, in addition to the power feed line, one or two or more signal lines, said joint (34) for the sensor body of said connector

- body includes a corresponding number of signal terminals, and an internal conductor (35a, 35c) coupling respective ones of the signal lines of said electric cord to the corresponding signal terminals of said joint for the sensor body is provided in said connector body. 5
12. The main connector according to claim 10, wherein
- said joint (33) for the neighboring connector of said connector body (3) is provided only on one side surface and, and no joint exist on the other side surface. 10
13. The main connector according to claim 10, wherein 15
- a connecting structure for establishing mechanical and electrical connections with a neighboring connector is provided at said joint (33) for the neighboring connector of said connector body (3); and 20
- the connecting structure has a recessed portion receiving a projecting portion of a neighboring connector, and is free of any projecting portion protruding toward a neighboring connector. 25
14. The main connector according to claim 10, wherein
- said sensor body (1) is a sensor body of a head separation type sensor including a fiber type photoelectric sensor, an ultrasonic sensor and a proximity sensor. 30
15. A sub connector, having a connector body (2) that can be detachably coupled to one of a plurality of sensor bodies (1) arranged aligned and adjacent to each other, 35
- said connector body including
- a joint (24) for a sensor body, including a power feed terminal for feeding power to the internal electric circuit of said sensor body,
- a joint (22) for a first neighboring connector, including a power receiving terminal for receiving power from one neighboring connector,
- a joint (23) for a second neighboring connector, including a power feed terminal for feeding power to the other neighboring connector, and
- an internal conductor (25a, 25b, 25c, 25d) for conducting the power received through the power receiving terminal included in said joint for the first neighboring connector, to the power feed terminal included in said joint for the sensor body and to the power feed terminal included in said joint for the second neighboring connector, inside the sub connector. 40 45 50 55
16. The sub connector according to claim 15, wherein
- an electric cord (8) including at least one signal line is introduced to said connector body (2), said joint (24) for the sensor body of said connector body includes a corresponding number of signal terminals, and an internal conductor (25a, 25c) coupling respective ones of the signal lines of said electric cord to the corresponding signal terminals of the joint of said sensor body is provided in said connector body.
17. The sub connector according to claim 15, wherein
- a connecting structure for establishing mechanical and electrical connections with a neighboring connector is provided at said joint (22) for the first neighboring connector and said joint (23) for the second neighboring connector;
- the connecting structure of said joint for the first neighboring connector has a projecting portion protruding toward a connector neighboring said joint for the first neighboring connector; and
- the connecting structure of said joint for the second neighboring connector has a recessed portion receiving the projecting portion of a neighboring connector, and is free of any projecting portion protruding toward a neighboring connector.
18. The sub connector according to claim 15, wherein
- said sensor body (1) is a sensor body of a head separation type sensor including a fiber type photoelectric sensor, an ultrasonic sensor and a proximity sensor.
19. A sensor system, including a plurality of sensor bodies (1) arranged aligned and adjacent to each other, each of said sensor bodies having an electric cord including at least a signal line connected via a connector (2, 3); wherein 40
- said sensor body and said connector are detachably coupled;
- each of said connector is provided with a power feed terminal for said sensor body and a detachable fitting for electrically connecting power feed terminals to each other is provided between the connectors; and
- the power supplied to the connector of any of said sensor body through the power supply line in the electric cord is distributed to the power feed terminal of another said sensor body through a row of connectors.
20. The sensor system according to claim 19, wherein

said sensor body (1) is a sensor body of a head separation type sensor including a fiber type photoelectric sensor, an ultrasonic sensor and a proximity sensor.

5

10

15

20

25

30

35

40

45

50

55

15




FIG. 2A




FIG. 2B




FIG. 3




FIG. 4A




FIG. 4B




FIG. 5A




FIG. 5B






FIG. 6








FIG. 9A




FIG. 9B




FIG. 10A




FIG. 10B





FIG. 11






FIG. 13A




FIG. 13B




FIG. 14




FIG. 15




FIG. 16




FIG. 17





FIG. 18



1. The first part of the paper discusses the importance of the study of the history of the United States. It is argued that the study of the history of the United States is essential for a full understanding of the country and its people. The author points out that the history of the United States is a complex and multifaceted one, and that it is important to study it from a variety of perspectives. The author also points out that the study of the history of the United States is important for the development of a sense of national identity and pride.

2. The second part of the paper discusses the importance of the study of the history of the United States. It is argued that the study of the history of the United States is essential for a full understanding of the country and its people. The author points out that the history of the United States is a complex and multifaceted one, and that it is important to study it from a variety of perspectives. The author also points out that the study of the history of the United States is important for the development of a sense of national identity and pride.

3. The third part of the paper discusses the importance of the study of the history of the United States. It is argued that the study of the history of the United States is essential for a full understanding of the country and its people. The author points out that the history of the United States is a complex and multifaceted one, and that it is important to study it from a variety of perspectives. The author also points out that the study of the history of the United States is important for the development of a sense of national identity and pride.

4. The fourth part of the paper discusses the importance of the study of the history of the United States. It is argued that the study of the history of the United States is essential for a full understanding of the country and its people. The author points out that the history of the United States is a complex and multifaceted one, and that it is important to study it from a variety of perspectives. The author also points out that the study of the history of the United States is important for the development of a sense of national identity and pride.

5. The fifth part of the paper discusses the importance of the study of the history of the United States. It is argued that the study of the history of the United States is essential for a full understanding of the country and its people. The author points out that the history of the United States is a complex and multifaceted one, and that it is important to study it from a variety of perspectives. The author also points out that the study of the history of the United States is important for the development of a sense of national identity and pride.



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 00 12 3068

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
A,D	US 5 818 123 A (IWASAKI KOUMEI ET AL) 6 October 1998 (1998-10-06)		H01R9/24
A	US 5 920 197 A (THOMPSON LAURENCE A ET AL) 6 July 1999 (1999-07-06)		
			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
			H01R
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 16 August 2001	Examiner Bertin, M
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

FPD 1-2/94 (1503.03.02 P04C01)

10

11

12

13